



Main

| | |
|------------------------------|---|
| Range of product | Easypact CVS400...630 NSX400...630 DC NSX400...630 PowerPact multistandard |
| Range | Compact |
| Device short name | Motor mechanism module |
| Product or component-type | Motor mechanism |
| Device application | Automatic spring charging |
| Range compatibility | Compact - Compact NSX Compact - Compact NSX DC PowerPact Multistandard |
| Product compatibility | PowerPact L-Frame |
| [In] rated current | 630 A 400 A |
| [Uc] control circuit voltage | 208...277 V AC 60 Hz 220...240 V AC 50/60 Hz |

Complementary

| | |
|-----------------------------|--|
| Control type | Standard |
| Control signal type | Impulse Maintained |
| Mounting mode | Fixed |
| Response time | < 600 ms - during opening time < 80 ms - during closing time |
| Maximum operating frequency | 4 per minute |
| Power consumption in VA | <= 500 VA - during closing time <= 500 VA - during opening time |
| Locking options description | 1 to 3 padlocks Ø 5 to Ø 8 Padlocking in OFF position |

Offer Sustainability

| | |
|----------------------------------|--|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 0908 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity |
| REACH | Reference not containing SVHC above the threshold |
| Product environmental profile | Available |
| Product end of life instructions | Available |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

Product Life Status : **Commercialised**

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.